

 SNC • LAVALIN	SETTINGS SHEET VARIABLE FREQUENCY DRIVE	Page 1 of 4
		ID: VFD-P-L2, VFD-P-L3

Document Code	508042-0000-47ED-0002				Professional Seal Original Sealed By: C. J. Reimer SNC-Lavalin Inc. Member #21968 2012/02/23 Rev. 00
Revision	00				
Client	City of Winnipeg				
Project	Montcalm Wastewater Pumping Station				
Description	P-L2 and P-L3 Lift Pumps				
Rev	Date	By	Checked	Approved	
00	2012/02/07	Brian Cleven	C. Reimer	C. Reimer	

VFD Data	Control Schematics: 1-0164L-E0020-002, 1-0164L-E0022-002		
	Size: 100 HP	Voltage: 600 V	Nominal Output Current: 108 A
	Manufacturer: ABB	Model: ACS800-04-0120-7	Nominal Efficiency: 98 %

Motor Data	Size: 100 HP	Voltage: 575 V	R.P.M: 1178
	Manufacturer: Teco Westinghouse	Model: Optim HE Plus	Serial Number: CPC43086-2
	FLA: 95.2 Code: G	Nominal Efficiency:	Service Factor: 1.15

Param. No.	Description	Set Point	Note	Rev.
99.01	LANGUAGE	ENGLISH		00
99.02	APPLICATION MACRO	USER 1		00
99.03	APPLIC RESTORE	N/A		00
99.04	MOTOR CTRL MODE	SCALAR		00
99.05	MOTOR NOM VOLTAGE	575 V		00
99.06	MOTOR NOM CURRENT	95.2 A		00
99.07	MOTOR NOM FREQ	60 Hz		00
99.08	MOTOR NOM SPEED	1178 rpm		00
99.09	MOTOR NOM POWER	74.6 kW		00
99.10	MOTOR ID RUN MODE	N/A		00
99.11	DEVICE NAME	N/A		00
10.01	EXT1 STRT/STP/DIR	DI1		00
10.02	EXT2 STRT/STP/DIR	DI1		00
10.03	REF DIRECTION	FORWARD		00
10.06	JOG SPEED SELECT	NOT SEL		00
10.07	NET CONTROL	0 (Inactive)		00
10.08	NET REFERENCE	0 (Inactive)		00
11.01	KEYPAD REF SEL	REF1	1	00
11.02	EXT1/EXT2 SELECT	DI3		00
11.03	EXT REF1 SELECT	AI1		00
11.04	EXT REF1 MINIMUM	18		00



SETTINGS SHEET VARIABLE FREQUENCY DRIVE

Param. No.	Description	Set Point	Note	Rev.
11.05	EXT REF1 MAXIMUM	60		00
11.06	EXT REF2 SELECT	AI2		00
11.07	EXT REF2 MINIMUM	0%		00
11.08	EXT REF2 MAXIMUM	100%		00
12.01	CONST SPEED SEL	DI5(SPEED5)		00
12.02	CONST SPEED 1	0		00
12.03	CONST SPEED 2	0		00
12.04	CONST SPEED 3	0		00
12.05	CONST SPEED 4	0		00
12.06	CONST SPEED 5	1178 RPM / 60 Hz		00
12.07	CONST SPEED 6	0		00
12.08	CONST SPEED 7	0		00
12.09	CONST SPEED 8	0		00
12.10	CONST SPEED 9	0		00
12.11	CONST SPEED 10	0		00
12.12	CONST SPEED 11	0		00
12.13	CONST SPEED 12	0		00
12.14	CONST SPEED 13	0		00
12.15	CONST SPEED 14	0		00
12.16	CONST SPEED 15	0		00
13.01	MINIMUM AI1	0 V		00
13.02	MAXIMUM AI1	10 V		00
13.03	SCALE AI1	100%		00
13.04	FILTER AI1	0.10 s		00
13.05	INVERT AI1	NO		00
13.06	MINIMUM AI2	4 mA		00
13.07	MAXIMUM AI2	20 mA		00
13.08	SCALE AI2	100%		00
13.09	FILTER AI2	0.10 s		00
13.10	INVERT AI2	NO		00
14.01	RELAY RO1 OUTPUT	READY		00
14.02	RELAY RO2 OUTPUT	RUNNING		00
14.03	RELAY RO3 OUTPUT	FAULT		00
14.04	RO1 TON DELAY	0		00
14.05	RO1 TOFF DELAY	0		00
14.06	RO2 TON DELAY	0		00
14.07	RO2 TOFF DELAY	0		00
14.08	RO3 TON DELAY	0		00
14.09	RO3 TOFF DELAY	0		00
15.01	ANALOGUE OUTPUT1	SPEED		00
15.02	INVERT AO1	NO		00
15.03	MINIMUM AO1	4 mA		00
15.04	FILTER AO1	0.10 s		00



SETTINGS SHEET VARIABLE FREQUENCY DRIVE

Param. No.	Description	Set Point	Note	Rev.
15.05	SCALE AO1	100%		00
15.06	ANALOGUE OUTPUT2	CURRENT		00
15.07	INVERT AO2	NO		00
15.08	MINIMUM AO2	4 Ma		00
15.09	FILTER AO2	0.10 s		00
15.10	SCALE AO2	63%	5	00
16.01	RUN ENABLE	YES		00
16.02	PARAMETER LOCK	OPEN		00
16.03	PASS CODE	N/A		00
16.04	FAULT RESET SEL	NOT SEL		00
16.05	USER MACRO IO CHG	NO SEL		00
16.06	LOCAL LOCK	ON		00
16.09	CTRL BOARD SUPPLY	INTERNAL 24V		00
16.10	ASSIST SEL	OFF		00
20.01	MINIMUM SPEED	N/A	2	00
20.02	MAXIMUM SPEED	N/A	3	00
20.03	MAXIMUM CURRENT	151 A		00
20.04	TORQ MAX LIM1	300%		00
20.05	OVERVOLTAGE CTRL	ON		00
20.06	UNDERVOLTAGE CTRL	ON		00
20.07	MINIMUM FREQ	18 Hz		00
20.08	MAXIMUM FREQ	60 Hz		00
20.11	P MOTORING LIM	300%		00
20.12	P GENERATING LIM	-300%		00
20.13	MIN TORQUE SEL	MIN LIM1		00
20.14	MAX TORQUE SEL	MAX LIM1		00
20.15	TORQ MIN LIM1	0.0%		00
21.01	START FUNCTION	AUTO		00
21.03	STOP FUNCTION	RAMP		00
21.04	DC HOLD	NO		00
21.08	SCALAR FLY START	NO		00
21.09	START INTRL FUNC	OFF2 STOP		00
21.10	ZERO SPEED DELAY	0.5 sec		00
22.01	ACC/DEC SEL	ACC/DEC 1		00
22.02	ACCEL TIME 1	5 sec		00
22.03	DECEL TIME 1	5 sec		00
22.06	ACC/DEC RAMP SHPE	0.0		00
27.01	BRAKE CHOPPER CTRL	OFF		00
30.01	AI<MIN FUNCTION	NO		00
30.02	PANEL LOSS	LAST SPEED		00
30.03	EXTERNAL FAULT	NOT SEL		00
30.04	MOTOR THERM PROT	NO		00
30.05	MOT THERM P MODE	DTC		00

Param. No.	Description	Set Point	Note	Rev.
30.10	STALL FUNCTION	FAULT		00
30.11	STALL FREQ HI	20 Hz		00
30.12	STALL TIME	20 sec		00
30.13	UNDERLOAD FUNC	NO		00
30.16	MOTOR PHASE LOSS	FAULT		00
30.17	EARTH FAULT	FAULT		00
30.18	COMM FLT FUNC	NO		00
30.19	MAIN REF DS T-OUT	3 sec		00
30.20	COMM FLT RO/AO	LAST VALUE		00
30.21	AUX DS T-OUT	3 sec		00
30.22	IO CONFIG FUNC	WARNING		00
30.23	LIMIT WARNING	0		00
31.01	NUMBER OF TRIALS	3		00
31.02	TRIAL TIME	30 SEC		00
31.03	DELAY TIME	3 SEC		00
31.04	OVERCURRENT	YES		00
31.05	OVERVOLTAGE	YES		00
31.06	UNDERVOLTAGE	YES		00
31.07	AI SIGNAL < MIN	YES		00
31.08	LINE CONV	YES		00

Notes
<ol style="list-style-type: none"> 1. Keypad to display reference in units of Hz when parameter 99.04 is SCALAR. 2. Parameter not applicable for SCALAR mode. See parameter 20.07. 3. Parameter not applicable for SCALAR mode. See parameter 20.08. 4. Use default value, or advise of appropriate value. 5. Scaling factor results in 20 mA output at 151.1 A motor current. 6. Minimum frequency to be determined via commissioning on site. 7. The Contractor is responsible for ensuring proper parameter values are utilized. SNC-Lavalin assumes no responsibility for incorrect parameter values that result in equipment damage.