

9. WIRE AND CONNECT NEW FIXTURES TO EXISTING VESTIBULE LIGHTING CIRCUIT AND CONTROL.
10. MAGNETIC DOOR LOCK POWER SUPPLY (BY OTHERS) TO BE WIRED AND CONNECTED TO DEDICATED CIRCUIT IN EXISTING PANEL 'MM'. DOORS TO RELEASE ON FIRE ALARM.
11. MAGNETIC DOOR LOCK KEY SWITCH (BY OTHERS) TO BE WIRED AND CONNECTED BY DIVISION 26. LOCKING DEVICES ARE TO RELEASE IMMEDIATELY UPON ACTIVATION OF A MANUALLY OPERATED SWITCH READILY ACCESSIBLE ONLY TO AUTHORIZED PERSONNEL. LOCATE SWITCH IN CENTRAL CONTROL ROOM IN BASEMENT. CONTROL ROOM IS LOCATED APPROXIMATELY BETWEEN GUIDES "D" & "E" AND "2" & "5". EXACT LOCATION OF SWITCH TO BE DETERMINED ON SITE WITH CONSULTANT AND OWNER. SWITCH BY HARDWARE SUPPLIER. DIVISION 26 TO WIRE AND CONNECT.
12. SMOKE DETECTORS TO BE PROGRAMMED TO START SMOKE EXHAUST FAN. FAN TO START ON ACTIVATION OF THE SECOND DETECTOR ONLY AFTER FIRST ONE ALARMS.
13. WIRE AND CONNECT NEW TYPE 'CC' FIXTURES TO EXISTING LIGHTING CIRCUIT IN ROOM. DIVISION 26 TO REMOVE EXISTING LIGHTING, SWITCH AND RELATED CONDUIT AND WIRING. SUPPLY AND INSTALL NEW BX CABLE.
14. WIRE AND CONNECT NOTED FIXTURES TO EXISTING EMERGENCY LIGHTING CIRCUIT.
15. WIRE AND CONNECT NEW EXIT LIGHT TO EXISTING EXIT LIGHT CIRCUIT. CIRCUIT TO BE PICKED UP FROM CLOSEST JUNCTION BOX IN BASEMENT. DO NOT WIRE FROM ANY AREA WITH ASBESTOS.

SMS ENGINEERING

SMS Engineering Ltd. Consulting Engineers
 770 Bradford Street Winnipeg MB Canada R3H 0H3
 Telephone 204.775.0291 Fax 204.772.2153
 sms@smseng.com

**CITY HALL ADMINISTRATION
 BUILDING MAIN FLOOR
 LOBBY RENOVATIONS
 510 MAIN STREET**

WINNIPEG

MANITOBA

ELECTRICAL NOTATION REVISION NOTE - #11

Drawn By	Approved By	Reference
BB	I.R.	E1.1
File No.	Date	Detail Sheet
07-106-01	FEB.5/08	ED-1